



Features

- ▶ Manages up to 99 SP-DVR systems
- ▶ Supports joystick Pan Tilt Zoom control
- ▶ Supports SP-DVR control
- ▶ Displays alarm information from connected DVR
- ▶ Connected via RS-485/232 or IP network
- ▶ 4 own alarm outputs
- ▶ Keyboard lock function
- ▶ Different log-in roles

Description

The SP-KEYBOARD is specially designed to offer a human intuitive control of PTZ-cameras as part of a local CCTV system based on SP-DVR/DVS system. The SP-KEYBOARD also supports full control of the SP-DVR/DVS systems. Using a local monitor connected to a SP-DVR functioning as a multiplexer the SP-KEYBOARD can select cameras and control PTZ functions. Alarms are displayed on the keyboards LC-Display and outputs can be activated for example for gate-control, switching lights, and equipment. According the diagrams the SP-Keyboard is connected through a serial interface either via corporate LAN/WAN or via internet.

Specifications

Control mode	RS-485 bus mode
Communication interface	1 x RJ-45 10M/100M UTP network port
	1 x RJ-45 RS-232 port
	2 x RS-485 port
Relay output	4 outputs
Power supply	+5VDC
Power consumption	6W
Working temperature	-10degC - +55degC
Working humidity	10% - 90%
Size	360mm * 190mm * 55mm
Weight	2.4 Kg

